
AIPCSM

IEC

Millisecond-level response.
Ready for highly dynamic AI loads.
Grid Forming for enhanced power stability.
Modular architecture for maximum availability.



AIPCSM
IEC



Preliminary

REFERENCES		FP5231MH
AC	AC Output Power (kVA/kW) @40°C [1]	5230
	AC Output Power (kVA/kW) @50°C [1]	4790
	Operating Grid Voltage (kV)	33 kV ±10%
	Operating Grid Frequency (Hz)	50 Hz
	Current Harmonic Distortion (THDi)	< 3% per IEEE 519
	Power Factor (CosPhi) [2]	0.5 leading ... 0.5 lagging
	Overload Capability	166% - 100 ms / 150% - 5 s / 120% - 8 s / 110% - 15 s
DC [4]	DC Voltage Range [3]	976 V – 1500 V
	Maximum DC Voltage	1500 V
	DC Voltage Ripple	< 3%
	Max. DC Continuous Current (A)	5468
	Max. DC Short Circuit Current (kA)	500 kA with a time constant of 1 ms
	Battery Technology	All types of batteries (BMS required)
EFFICIENCY & AUX. SUPPLY	Efficiency (Max) (η)	98.00% including MV transformer
	Euroeta (η)	97.53% including MV transformer
CABINET	Dimensions [WxDxH] (ft)	23.5 x 6.5 x 7.2
	Dimensions [WxDxH] (m)	7.15 x 2.0 x 2.2
	Weight (lbs)	32628
	Weight (kg)	14800
	Type of Ventilation	Forced air cooling
ENVIRONMENT	Degree of Protection	IP55
	Operating Temperature Range	From -40 °C to +60 °C, >40 °C power derating (optional below -25 °C)
	Operating Relative Humidity Range	From 4% to 100%
	Storage Temperature Range	From -40 °C to +60 °C
	Max. Altitude (above sea level)	1000 m
CONTROL	Communication Protocol	Modbus TCP
	Power Plant Controller	Optional
	Keyed ON/OFF Switch	Standard
PROTECTIONS	Ground Fault Protection	Insulation monitoring device
	Humidity Control	Active heating
	General AC Protection & Disconnection	36 kV MV switchgear (2L+V)
	General DC Protection & Disconnection	High-speed fuses, Motorized DC disconnect switches [5]
	Overvoltage Protection	Type II for AC and Type I+II for DC
STANDARDS	Safety	IEC 62109-1 / IEC 62109-2 / IEC 62477-1 / IEC 62477-2
	Utility Interconnect [6]	IEC 62116 / G99 / VDE 4110-4120-4130 / CEI 0-16 / NTS 2.1 / EN 50549

NOTES

[1] Values at 1.00·Vac nom and CosPhi=1. Consult Power Electronics for derating curves.
[2] Consult P-Q charts available: $Q(kVAr)=\sqrt{(S(kVA)^2-P(kW)^2)}$.
[3] Consult Power Electronics for derating curves. In the event of overvoltage in the grid, the minimum DC voltage will vary proportionally with the AC voltage.
[4] 2 and 4 independent DC inputs available. Consult Power Electronics for further information.
[5] Battery short circuit disconnection must be done on the battery side.
[6] Consult Power Electronics for other applicable standards / grid codes.

The content of this document is periodically updated. Power Electronics reserves the right to modify all or part of the contents of this document without prior notice.

POWER ELECTRONICS